Wind Speed Sensor



EQ - FST201 Wind Speed Sensor is based on Hall Effect. The cup turns round once be blown. The wind speed variable transfer into relative signal output. The base is made of high strength alloy and finish by surface treatment and is featured with water proof, corrosion resisting. It can be used in harsh environment.

High - Performance Digital Circuit is built in FST Wind Speed Sensors. It carefully designed the working condition of RFI & EMI resistance and the surge voltage. It is featured with strong RFI & EMI resistance, wide power range and polarity protection, meeting ICE. CE (EMC) requirement. It can meet demands of working aloft, construction machinery, port operation, wind power generation system.

Features

- Excellent Resistance against impact, overload, shock and erosion
- Small and Exquisite, Easy to take, Simple to install
- · Alloy Material finish, Reasonable Structure design and nice outlook quality
- · Stainless steel wind cup, Anti Wind load can reach 70m/s

Applications

- Working Aloft Testing and Control
- · Engineering Machine Testing and Control
- · Weather Station and Environment Protection Testing and Control
- Port and wharf Environment Testing and Control



Specifications


Testing Range	0.5m/s ~ 50m/s				
Accuracy	± 0.5 m/s (<5m/s), ± 3% FS (≥ 5m/s)				
Start Wind Speed	≤ 0.5 m/s				
Limit Wind Speed	Max: 70m/s 30min				
Output	Pulse signal (HZ), 05VDC, 4~20mA				
Working Voltage	5VDC, 24VDC, 12 ~ 36VDC (common 24VDC)				
Working Environment	Temp20 °C ~ +85 °C Humidity < 95 % RH				
Electrical Connection	M12 with 10 Mtrs Cable				
Environmental Protection	IP65 with CE Mark				

M12 Connection	Potential Lead	Output Signal	Serial NO	Wiring Method	
20 01 30 04	3-Wire	Current mode	1	+Vcc	Brown
			2	+Vout	White
			3	GND	Blue
			4	PE	Black
	3-Wire	Voltage mode	1	+Vcc	Brown
			2	+Vout	White
			3	GND	Blue
			4	PE	Black
	3-Wire	Pulse mode	1	+Vcc	Brown
			2	+P^ovt	White
			3	GND	Blue
			4	PE	Black

Wind Speed Sensor



Dimension



Ordering Code

